

# **Red LED**



L10762

## **Resonant cavity LED for POF data communication**

The L10762 is a red LED designed for POF data communications. A microball lens is bonded to the LED chip to enhance fibre-coupling efficiency.

#### Features

- Improved fiber-coupling efficiency
   A microball lens is bonded to the LED chip surface to enhance the coupling efficiency to optical fibers.
   Fiber end output power \*² was boosted about 7 times higher than our conventional type.
- High-speed response: 70 MHz

### - Applications

POF (plastic optical fiber) data communication

#### - Absolute maximum ratings

Parameter	Symbol	Value	Unit
Reverse voltage	VR	3	V
Forward current	IF	50	mA
Pulsed forward current*1	IFP	80	mA
Operating temperature	Topr	-30 to +85	°C
Storage temperature	Tsta	-40 to +100	°C

<sup>\*1:</sup> Pulse width: 1 µs, Duty ratio=50 %

Note: Exceeding the absolute maximum ratings even momentarily may cause a drop in product quality. Always be sure to use the product within the absolute maximum ratings.


#### **➡** Electrical and optical characteristics (Ta=25 °C)

Parameter	Symbol	Condition	Min.	Тур.	Max.	Unit
Peak emission wavelength	λр	IF=20 mA	640	660	670	nm
Spectral half width	Δλ	IF=20 mA	-	15	25	nm
Fiber end output*2	Pf	IF=20 mA	0.7	1.0	-	mW
Forward voltage	VF	IF=20 mA	-	1.9	2.4	V
Reverse current	IR	VR=3 V	-	-	10	μΑ
Cut-off frequency*3	fc	IF=20 mA ±1 mAp-p	60	70	-	MHz


<sup>\*2:</sup> Plastic fiber: 1 mm in core diameter, 1 meter in length, and Z (distance between cap surface and fiber end)=0.3 mm

<sup>\*3:</sup> Frequency at which the radiant output drops by 3 dB relative to the output at 100 kHz

#### **Emission spectrum**




## Fiber end output vs. forward current




KLEDB0331EA

#### Forward current vs. forward voltage




#### Fiber end output vs. ambient temperature




KLEDB0330EA

#### - Allowable forward current vs. ambient temperature




#### **Frequency characteristics**



KLEDB0318EA

#### Fiber coupling characteristics



(Typ. Ta=25 °C, I<sub>F</sub>=20 mA, X, Y=0 mm, plastic fiber: 1 mm in core diameter)

80

80

40

0

0

0

0

0

0

0

0

1.6


2.0

Z direction

Distance between fiber end and cap surface Z (mm)  $\,$ 

KLEDB0314EA

#### Dimensional outline (unit: mm)



#### - Related information

www.hamamatsu.com/sp/ssd/doc\_en.html

- Precautions
- · Disclaimer
- · Metal, ceramic, plastic products
- Technical information
- · LED

Information described in this material is current as of February, 2016.

Product specifications are subject to change without prior notice due to improvements or other reasons. This document has been carefully prepared and the information contained is believed to be accurate. In rare cases, however, there may be inaccuracies such as text errors. Before using these products, always contact us for the delivery specification sheet to check the latest specifications.

The product warranty is valid for one year after delivery and is limited to product repair or replacement for defects discovered and reported to us within that one year period. However, even if within the warranty period we accept absolutely no liability for any loss caused by natural disasters or improper product use. Copying or reprinting the contents described in this material in whole or in part is prohibited without our prior permission.

# MAMAI

www.hamamatsu.com

HAMAMATSU PHOTONICS K.K., Solid State Division
1126-1 Ichino-cho, Higashi-ku, Hamamatsu City, 435-8558 Japan, Telephone: (81) 53-434-3311, Fax: (81) 53-434-5184 U.S.A.: Hamamatsu Corporation: 360 Foothill Road, Bridgewater, N.J. 08807, U.S.A., Telephone: (1) 908-231-0960, Fax: (1) 908-231-1218

U.S.A.: Harmantsus Corporation: 360 Footinin Road, Bridgewater, N.J. 08607, U.S.A., Helphone: (1) 906-231-9560, Fax: (1) 906-231-1218
Germany: Harmantsus Urbotonics Details Statistical and Embit: Arzbergersters 1.0, D-82211 Herrsching am Ammersee, Germany, Telephone: (49) 8152-375-0, Fax: (49) 8152-265-8
France: Harmantsu Photonics France S.A.R.L.: 19, Rue du Saule Trapu, Parc du Moulin de Massy, 91882 Massy Cedex, France, Telephone: 33-(1) 69 53 71 00, Fax: 33-(1) 69 53 71 10
United Kingdom: Harmantsus Photonics UK Limited: 2 Howard Court, 10 Tewin Road, Welwyn Garden City, Hertfordshire AL7 1BW, United Kingdom: Telephone: (44) 1707-294888, Fax: (44) 1707-325777
North Europe: Harmantsus Photonics Norden AB: Torshamnsgatan 35 16440 Kista, Sweden, Telephone: (46) 8-509-031-00, Fax: (46) 8-509-031-01
Italy: Harmantsus Photonics Italia S.r.L: Strada della Moia, 1 int. 6, 20020 Arese (Milano), Italy, Telephone: (39) 02-93581733, Fax: (39) 02-93581741

China: Hamamatsu Photonics (China) Co., Ltd.: B1201, Jiaming Center, No.27 Dongsanhuan Beilu, Chaoyang District, Beijing 100020, China, Telephone: (86) 10-6586-6006, Fax: (86) 10-6586-2866